

28,<sup>65 EUR</sup>

Item no.: 326453 shipping weight: 0.10 kg Manufacturer: Arduino

Item no.: 326453 ABX00012 - Arduino MKR ZERO (I2S bus & SD for sound, music & digital audio data)



## Product Description

Arduino MKR ZERO (I2S bus & SD for sound, music & digital audio data)

The MKR ZERO brings you the power of a Zero in the smaller format established by the MKR form factor. The MKR ZERO board acts as a great educational tool for learning about 32-bit application development. It has an on-board SD connector with dedicated SPI interfaces (SPI1) that allows you to play with MUSIC files with no extra hardware! The board is powered by Atmels SAMD21 MCU, which features a 32-bit ARM Cortex(R) M0+ core.

Warning: Unlike most Arduino & Genuino boards, the MKRZero runs at 3.3 V. The maximum voltage that the I/O pins can tolerate is 3.3 V. Applying voltages higher than 3.3 V to any I/O pin could damage the board.

The board contains everything needed to support the microcontroller; simply connect it to a computer with a micro-USB cable or power it by a LiPo battery. The battery voltage can also be monitored since a connection between the battery and the analog converter of the board exists.

- Microcontroller: SAMD21 Cortex-M0+ 32 bit low-power ARM MCU
- Nicrocontroller. SAND21 Context and + 32 bit tow-power ARM MC
   Board power supply (USB/VIN): 5 V
   Supported battery(\*): Li-Po single cell, 3.7 V, 700 mAh minimum
   DC current for 3.3 V pin: 600 mA
   DC current for 5 V pin: 600 mA
   Circuit constraint outbace: 2.3 V

- Digital I/O pins: 22
- Digital #0 pins. 22
  PWM pins: 12 (0, 1, 2, 3, 4, 5, 6, 7, 8, 10, A3- or 18-, A4- or 19)
  UART: 1
- SPI: 1
  I2C: 1

- Analog input pins: 7 (ADC 8/10/12 bit)
  Analog output pins: 1 (DAC 10 bit)
  External interrupts: 8 (0, 1, 4, 5, 6, 7, 8, A1- or 16-, A2- or 17)
  DC current per I/O pin: 7 mA
  Flash memory: 256 KB

- Flash memory for bootloader: 8 KB
  SRAM: 32 KB
- EEPROM: no
- Clock speed: 32.768 kHz (RTC), 48 MHz
  Built-in LEDs: 32
  Full-speed USB device and embedded host

## Specifications



Scan this QR code to view the product All details, up-to-date prices and availability