

Rem no.: 384312 APBM3M - QuMax for Peplink MAX BR1 Mini (HW3)



from 162,71 EUR

Item no.: 384312 shipping weight: 2.80 kg Manufacturer: QuWireless

Product Description

INTEGRATED MULTI-BAND 5G DIRECTIONAL ANTENNA + WI-FI OMNI ANTENNA + GPS ANTENNA + PLACE TO INSTALL PEPLINK MAX BR1 MINI (HW3) & M2M (ALL-IN-ONE)QuMax antenna for Peplink MAX BR1 Mini (HW3) & M2M router is a perfect outdoor device for improving the signal in rural/suburban and locations where the mobile signal is weak. It has embedded directional 5G, omni Wi-Fi and GPS antenna. If you use MAX BR1 Mini (HW3) or M2M with QuMax antenna, you get an integrated complete solution with embedded router and multi band antennas in one enclosure. 5G / LTE ANTENNA SPECIFICATIONFREQUENCY- 617 - 960 MHz - 1.7 - 2.7 GHz - 3.3 - 4.6 GHz - 4.7 - 6.0 GHz GAIN- 617 - 960 MHz - 1.6 dBi- 1.7 - 2.7 GHz - 7 dBi- 3.3 - 4.6 GHz - 4.7 - 6.0 GHz GAIN- 617 - 960 MHz - 1.6 dBi- 1.7 - 2.7 GHz - 7 dBi- 3.3 - 4.6 GHz - 4.7 - 6.0 GHz - 5.5 dBisUPPORTED LTE BANDS- 1, 2, 3, 4, 5, 7, 8, 9, 10, 12, 13, 14, 17, 18, 19, 20, 22, 25, 26, 27, 28, 29, 30, 33, 34, 35, 36, 37, 38, 39, 40, 41, 42, 43, 44, 46, 47, 48, 49, 52, 53, 65, 66, 67, 68, 69, 71, 85, 103, 106SUPPORTED 5G BANDS- 11, n2, n3, n5, n7, n8, n12, n13, n14, n18, n20, n25, n26, n28, n29, n30, n34, n38, n39, n40, n41, n46, n47, n48, n53, n65, n66, n67, n71, n77, n78, n79, n80, n81, n82, n83, n84, n85, n86, n89, n90, n95, n97, n98, n100, n101, n256VSWR - <2.00, max <3.00BEAMWIDTH- 80°/80° ±15°POLARIZATION- X (+-45degrees)IMPEDANCE- 50 ?WI-FI ANTENNA SPECIFICATIONFREQUENCY- 2.4 - 2.5 GHz - 4.7 - 6.0 GHzGAIN- 2.4 - 2.5 GHz : 6 dBi- 4.7 - 6.0 GHz : 7 dBi/SWR < 1.70, max < 2.00BEAMWIDTH- 360°/25°POLARIZATION- VerticalIMPEDANCE- 50 ?WI-FI ANTENNA

Specifications

Scan this QR code to view the product All details, up-to-date prices and availability

